

Sonnet Thunderbolt 4 Docks and Hub - Monitor Support

Host Computer	1st Thunderbolt Port	2nd Thunderbolt Port	USB 3 Port
14-inch MacBook Pro with M1 Pro (2021) or M2 Pro/Max (2023) 16-inch MacBook Pro with M1 Pro/Max (2021) or M2 Pro/Max (2023) Mac mini with M2 Pro (2023) Mac Studio with M1 Max/Ultra (2022) or M2 Max/Ultra (2023)	<ul style="list-style-type: none"> • 6K Apple Pro Display XDR • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	<ul style="list-style-type: none"> • 6K Apple Pro Display XDR • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	With Sonnet DisplayLink Adapter ² : <ul style="list-style-type: none"> • 2x 4K@60Hz • 2x 1440p@144Hz • 2x 1080p@144Hz
MacBook Air with M1 (2020) or M2 (2022, 2023) 13-inch MacBook Pro with M1 (2020) or M2 (2022) Mac mini with M1 (2020) or M2 (2023) iMac with M1 (2021) or M2 (2023)	<ul style="list-style-type: none"> • 6K Apple Pro Display XDR • 5K@60Hz • 4K@144Hz • 1440p@144Hz • 1080p@144Hz 	—	With Sonnet DisplayLink Adapter ² : <ul style="list-style-type: none"> • 2x 4K@60Hz • 2x 1440p@144Hz • 2x 1080p@144Hz
16-inch MacBook Pro (2019) 15-inch MacBook Pro (2018 or later) iMac (2019 or later) MacPro (2019)	<ul style="list-style-type: none"> • 6K Apple Pro Display XDR • 5K@60Hz • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	<ul style="list-style-type: none"> • 6K Apple Pro Display XDR • 5K@60Hz³ • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	With Sonnet DisplayLink Adapter ² : <ul style="list-style-type: none"> • 2x 4K@60Hz • 2x 1440p@144Hz • 2x 1080p@144Hz
13-inch MacBook Pro with four Thunderbolt 3 ports (2020) MacBook Air (2020)	<ul style="list-style-type: none"> • 6K Apple Pro Display XDR • 5K@60Hz • 4K@60Hz • 1440p up to 144Hz • 1080p up to 240Hz 	<ul style="list-style-type: none"> • 6K Apple Pro Display XDR • 4K@60Hz • 1440p up to 144Hz • 1080p up to 240Hz 	With Sonnet DisplayLink Adapter ² : <ul style="list-style-type: none"> • 2x 4K@60Hz • 2x 1440p@144Hz • 2x 1080p@144Hz
15-inch MacBook Pro (2016–2017) 13-inch MacBook Pro (2016–2019) 13-inch MacBook Pro (2016–2019) 13-inch MacBook Pro with two Thunderbolt 3 ports (2020) MacBook Air (2018–2019) iMac/iMac Pro (2017) Mac mini (2018)	<ul style="list-style-type: none"> • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	<ul style="list-style-type: none"> • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	With Sonnet DisplayLink Adapter ² : <ul style="list-style-type: none"> • 2x 4K@60Hz • 2x 1440p@144Hz • 2x 1080p@144Hz
Any Mac with older macOS version (10.15 and previous)	X	X	X
Windows Thunderbolt 4 or USB4 Computer Windows Thunderbolt 3 Computer with Intel 8th Gen or Newer CPU	<ul style="list-style-type: none"> • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	<ul style="list-style-type: none"> • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	With Sonnet DisplayLink Adapter ² : <ul style="list-style-type: none"> • 2x 4K@60Hz • 2x 1440p@144Hz • 2x 1080p@144Hz
Windows Thunderbolt 3 Computer with Intel 7th Gen or Older CPU	X	X	X
iPad Pro with Thunderbolt Ports ⁴ (iOS 15+)	<ul style="list-style-type: none"> • 6K Apple Pro Display XDR • 5K@60Hz • 4K@60Hz • 1440p@60Hz • 1080p@60Hz 	—	—
ChromeBook with Thunderbolt 4 or USB4 Ports (current version)	<ul style="list-style-type: none"> • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	<ul style="list-style-type: none"> • 4K@60Hz • 1440p@144Hz • 1080p@240Hz 	—

1. With Sonnet Thunderbolt Dual DisplayPort or Dual HDMI Adapter (sold separately).

2. With Sonnet DisplayLink Dual DisplayPort or Dual HDMI Adapter (sold separately).

3. You cannot hotplug the 2nd 5K display. You must first connect both displays and then hotplug Thunderbolt to the computer.

4. Mirrors internal display.

03 Oct 2024

©2021-2024 Sonnet Technologies, Inc. All Rights Reserved.